

AC/DC DIGITAL POWER METER CODE 9670-PM70

- Basic accuracy: 0.2%
- AC/DC universal, input signal bandwidth: DC, 15Hz-5kHz
- High measurement speed, up to 0.1s refresh rate
- Voltage and current ratio function
- Sound and light alarm for voltage, current, power over the limits
- Standard RS232 interface to support test automation and data transmission



SPECIFICATION

Measurement parameters	voltage (U), current (I), active power (P), reactive power (Q), apparent power (S), power factor (λ), phase angle (Φ), voltage frequency (f), voltage peak (Vpk), current peak (Apk), electric energy (Wh), current integration (Ah), electric energy time (Time)	
Wiring method	single phase	
Voltage range	15/30/60/150/300/600V	
Current range	100mA/200mA/500mA/1A/2A/5A/10A/20A	
Voltage	Display range	0.15V~600V
	Accuracy (23±5°C)	DC, 15Hz≤f≤5kHz: $\pm(0.1\% \times \text{display} + 0.1\% \times \text{range})$
Current	Display range	0.5mA~20A
	Accuracy (23±5°C)	DC, 15Hz≤f≤5kHz: $\pm(0.1\% \times \text{display} + 0.1\% \times \text{range})$
Active power	Display range	1.0mW~12kW
	Accuracy (23±5°C)	DC, 15Hz≤f≤5kHz: PF>0.5: $\pm(0.1\% \times \text{display} + 0.1\% \times \text{range})$ PF≤0.5: $\pm(0.25\% \times \text{display} + 0.25\% \times \text{range})$
Frequency	Display range	15Hz~5kHz
	Accuracy (23±5°C)	$\pm(0.1\% \times \text{display})$ (voltage amplitude should be greater than 10% of range)
Electric energy	Display range	0~9999MWh
	Accuracy (23±5°C)	$\pm(0.5\% \times \text{display})$
Current integration	Display range	0~9999MAh
	Accuracy (23±5°C)	$\pm(0.5\% \times \text{display})$
Power factor	$\pm(0.010 \sim 1.000)$	
Ratio range(voltage, current)	0.1~6000	
Interface	RS232 interface, supports MODBUS and ASCII code protocols	
Power supply	AC: 100V~240V, 50/60Hz	
Dimension (LxWxH)	281x213x99mm	
Weight	2550g	

STANDARD DELIVERY

Main unit	1 pc
RS232 communication cable	1 pc